

High Energy Density Bobbin AA Cell

Primary Lithium Battery

ER14505 3.6V 2.7Ah

3.6V Primary lithium-thionyl chloride (Li-SOCl2) Energy Type




For low drain/long term operating applications requesting superior voltage response in -55°C ~+ 85°C environments

Cell size references	U	M3-R6-AA
Alternative models	LS14500/LST14500/LS14500C/TL4903/TL5903	3/SB-AA01
Electrical characteristics (Typical values relative to cells stored for Nominal capacity (At 1mA +20°C,2.0V cut off.The capacity)	one year or less at +30°C max.) restored varies according to current,temperature,	2.7Ah cut off)
Open circuit voltage(At 20°C)		3.66V
Nominal voltage (At 1mA +20°C)		3.6 V
Max. continuous current (at +20°C)		100mA
Typical Max. Pulse current (at +20°C)		200mA
20°C from cells with 20µA base current, yie	20mA/0.1second pulses drained every 2min at belding voltage readings above 3.0V. The readings as, temperature and cell's previous history. Fitting and ded in severe conditions.)	
Storage (recommended)	·	+30°CMax
Operating temperature range (High and low temperature will lower the o	capacity and load voltage.)	-55°C~+85°C
Physical characteristics		
Diameter(Max)		14.5mm(0.55in)
Height(Max)		50.5mm(2in)
Typical weight		17g(0.557oz)
Available terminal suffix	radial tabs,radial pins,axial leads,flying leads	

Shenzhen Wecodo Technology Co.,Ltd

ER14505



Key features

- >High and stable load voltage
- >Superior drain capacity
- >Low self-discharge rate (less than 1% after 1 year of storage at 20°C)
- >Stainless steel container
- >Hermetic glass-to-metal sealing
- >Laser welding
- >Non-flammable electrolyte

Main applications

- >Radiocommunication and other similar applications
- >Alarms and security systems
- >Beacons and emergency location transmitters
- >GPS equipment
- >Metering systems
- >Led lighting applications
- >Others

Storage

- >Cells should be stored in a clean &dry(less than 30% RH) area
- >Temp. should not exceed +30°C

Warning

- >Do not use if cell casing is mangled
- >Do not use different model of cell in series
- >Soldering the tag should be finished in few seconds
- >Do not try to recharge

