

<b>DMX 512</b>	<b>2CH</b>
Dimmer: W1, W2, W3, W4, from dark to bright	CH 1
Strobe: W1, W2, W3, W4, from slow to fast	CH 2

<b>DMX 512</b>	<b>1CH</b>
Dimmer: W1, W2, W3, W4, from dark to bright	CH 1



**YR-E100W\*4 WW**

**COB BLINDER 4**



**Please read this manual carefully  
before you use this machine**

Electrical	Voltage	110V ~ 240V, 50-60HZ
	Power consumption	500W
Light source	LED	100WX4PCS
	Color	3200K
Control mode	DMX512	8/4/2/1CH OPTIONAL
	Master/slave	√
	Manual control	√
	Sound Active	√
	Auto	√
	Light Body Material	aluminum
Optical system	Lens Angle	60 °
	Strobe	1-10t/s
	Dimmer frequency	1000Hz
	driver electric current	700mA
Phisical	light size	37*35*19cm
	Net weight	8.25kg
Environment & safety	Stock	dry place
	Min working temperature	-20°C
	Max working temperature	40°C

**CHANNEL CHART**

<b>DMX512</b>	<b>8CH</b>	<b>4CH</b>
Dimmer: W1, W2, W3, W4, from dark to bright	CH 1	
W1 Dimmer: from dark to bright	CH 2	CH 1
W2 Dimmer: from dark to bright	CH 3	CH 2
W3 Dimmer: from dark to bright	CH 4	CH 3
W4 Dimmer: from dark to bright	CH 5	CH 4
Strobe: from slow to fast	CH 6	
Function selection: 0-20 no use, 21-35 jump change1.....121-135 jump change 6,136-150 fade run 1.....226-240 fade run 6, 241-255 voice control	CH 7	
Function speed: from slow to fast	CH 8	